

Europäisches Patentamt

European Patent Office

Office européen des brevets



(11)

EP 1 018 666 A1

(12)

EUROPEAN PATENT APPLICATION

published in accordance with Art. 158(3) EPC

(43) Date of publication:

12.07.2000 Bulletin 2000/28

(21) Application number: 99931502.1

(22) Date of filing: 23.07.1999

(51) Int. Cl.⁷: G02F 1/35, H04B 10/17

(86) International application number:

PCT/JP99/03944

(87) International publication number:

WO 00/05622 (03.02.2000 Gazette 2000/05)

(84) Designated Contracting States:

DE FR GB IT

(30) Priority: 23.07.1998 JP 20845098

27.07.1998 JP 21082298

12.02.1999 JP 3476999

12.02.1999 JP 3483399

(71) Applicant:

The Furukawa Electric Co., Ltd.
Tokyo 100-8322 (JP)

(72) Inventors:

• AKASAKA, Youichi,
The Furukawa Electric Co., Ltd
Tokyo 100-8322 (JP)

• EMORI, Yoshihiro,

The Furukawa Electric Co., Ltd
Tokyo 100-8322 (JP)

• NAMIKI, Shu,

The Furukawa Electric Co., Ltd
Tokyo 100-8322 (JP)

(74) Representative:

Hillier, Peter et al
Reginald W. Barker & Co.,
Cliffords Inn
Fetter Lane
London EC4A 1BY (GB)

(54) RAMAN AMPLIFIER, OPTICAL REPEATER, AND RAMAN AMPLIFICATION METHOD

(57) A Raman amplifier comprises a pumping light producing means (1) for producing pumping lights. The pumping lights are multiplexed with a signal light propagated through an optical fiber (2) so as to give the signal light a Raman gain. The means (1) is constituted of a semiconductor laser of Fabri-Perot, DFB, or DBR type and an MOPA (3). The center wavelengths of the pumping lights are different from each other, and the intervals between them are 6 nm to 35 nm. An optical repeater provided in an optical fiber transmission line (8) compensates the loss caused by the optical fiber transmission line (8) and includes the Raman amplifier (9) used for the compensation. A Raman amplification method for Raman-amplifying a signal light by sending the signal light and pumping lights having mutually different center wavelengths through an optical fiber serving as a Raman-amplification medium, in which the power of the pumping light having a shorter wavelength is higher.




FIG. 1

EP 1 018 666 A1

Description

BACKGROUND OF THE INVENTION

5 Field of the Invention

[0001] The present invention relates to a Raman amplifier capable of being used for amplification of optical signal in various optical communication systems, and optical repeater and Raman amplification method using such a Raman amplifier, and more particularly, it relates to Raman amplifier, optical repeater and Raman amplification method suitable for amplification of wavelength division multiplexing signals.

Related Background Art

[0002] Almost all of optical amplifiers used with present optical fiber communication systems are rare earth doped fiber amplifiers. Particularly, erbium doped optical fiber amplifier (referred to as "EDFA" hereinafter) using Er (erbium) doped fibers have been used frequently. However, a practical gain wavelength band of the EDFA has a range from about 1530 nm to 1610 nm (refer to "Electron. Lett.," vol.33, no.23, pp.1967-1968). Further, the EDFA includes gain having wavelength dependency, and, thus, when it is used with wavelength division multiplexing signals, difference in gain is generated in dependence upon a wavelength of optical signal. Fig. 23 shows an example of gain wavelength dependency of the EDFA. Particularly, in wavelength bands smaller than 1540 nm and greater than 1560 nm, change in gain regarding the wavelength is great. Accordingly, in order to obtain given gain (in almost cases, gain deviation is within 1 dB) in the entire band including such wavelength, a gain flattening filter is used.

[0003] The gain flattening filter is a filter designed so that loss is increased in a wavelength having great gain, and the loss profile has a shape substantially the same as that of the gain profile. However, As shown in Fig. 24, in the EDFA, when magnitude of average gain is changed, since the gain profile is also changed as shown by curves a, b and c, in this case, the optimum loss profile of the gain flattening filter is also changed. Accordingly, when the flattening is realized by a gain flattening filter having fixed loss profile, if the gain of the EDFA is changed, the flatness will be worsened.

[0004] On the other hand, among optical amplifiers, there is an amplifier referred to as a Raman amplifier utilizing Raman scattering of an optical fiber (refer to "Nonlinear Fiber Optics, Academic Press). The Raman amplifier has peak gain in frequency smaller than frequency of pumping light by about 13 THz. In the following description, it is assumed that pumping light having 1400 nm band is used, and the frequency smaller by about 13 THz will be expressed as wavelength longer by about 100 nm. Fig. 25 shows wavelength dependency of gain when pumping light having central wavelength of 1450 nm is used. In this case, peak of gain is 1550 nm and a band width within gain deviation of 1 dB is about 20 nm. Since the Raman amplifier can amplify any wavelength so long as an pumping light source can be prepared, application of the Raman amplifier to a wavelength band which could not be amplified by the EDFA has mainly be investigated. On the other hand, the Raman amplifier has not been used in the gain band of the EDFA, since the Raman amplifier requires greater pump power in order to obtain the same gain as that of the EDFA. When the pumping light having great power is input to a fiber to increase the gain, stimulated Brillouin scattering may be generated. Increase amplification noise caused by the stimulated Brillouin scattering is one of the problems which makes it difficult to use the Raman amplifier, the Japanese Patent Laid-open No. 2-12986 (1990) discloses an example of a technique for suppressing the stimulated Brillouin scattering in the Raman amplifier.

[0005] Further, the Raman amplifier has polarization dependency of gain and amplifies only a component (among polarized wave components) coincided with the polarized wave of the pumping light. Accordingly, it is required for reducing unstability of gain due to polarization dependency, and, to this end, it is considered that a polarization maintaining fiber is used as a fiber for amplifying or an pumping light source having random polarization condition.

[0006] Furthermore, enlargement of the gain band is required in the Raman amplifier. To this end, Japanese Patent Publication No. 7-99787 (1995) teaches in Fig. 4 that the pumping light is multiplexed with appropriate wavelength interval. However, this patent does not disclose concrete values of the wavelength interval. According to a document (K. Rot-twitz, OFC98, PD-6), a Raman amplifier using a plurality of pumping lights having different wavelengths was reported; however, attempt in the viewpoint of the fact that the gain deviation is reduced below 1 dB was not considered.

[0007] On the other hand, there is an optical repeater for simultaneously compensating for transmission loss and chromatic dispersion in an optical fiber transmission line, which optical repeater is constituted by combination of an Er doped fiber amplifier (EDFA) and a dispersion compensating fiber (DCF). Fig. 46 shows a conventional example in which a dispersion compensating fiber A is located between two Er doped fiber amplifiers B and C. The first Er doped fiber amplifier B serves to amplify optical signal having low level to a relatively high level and has excellent noise property. The second Er doped fiber amplifier C serves to amplify the optical signal attenuated in the dispersion compensating fiber A to the high level again and has a high output level.

[0008] By the way, on designing the optical repeater, it is required that a repeater input level, a repeater output level and a dispersion compensating amount (loss in the dispersion compensating fiber A) be set properly, and, there is limitation that the input level of the dispersion compensating fiber A has an upper limit, because, when the input power to the dispersion compensating fiber A is increased, influence of non-linear effect in the dispersion compensating fiber A is also increased, thereby deteriorating the transmission wave form considerably. The upper limit value of the input power to the dispersion compensating fiber A is determined by self phase modulation (SPM) in one wave transmission and by cross phase modulation (XPM) in WDM transmission. Thus, regarding the optical repeater, an optical repeater having excellent gain flatness and noise property must be designed in consideration of the several variable factors.

[0009] Fig. 47 shows a signal level diagram in the repeater. Gain G_1 [dB] of the first Er doped fiber amplifier B is set to a difference between an input level P_{in} [dB] of the repeater and an input upper limit value P_d [dB] to the dispersion compensating fiber A. Gain G_2 [dB] of the second Er doped fiber amplifier C is set to $(G_r + L_d - G_1)$ [dB] from loss L_d [dB] in the dispersion compensating fiber A, gain G_r [dB] of the repeater and the gain G_1 [dB] of the first Er doped fiber amplifier B. Since these design parameters are varied for each system, the values G_1 [dB] and G_2 [dB] are varied for each system, and, accordingly, the Er doped fiber amplifiers B, C must be re-designed for each system. The noise property in such a system is deeply associated with the loss L_d [dB] in the dispersion compensating fiber A, and it is known that the greater the loss the more the noise property is worsened. Further, at present, a gap from the designed value in loss in the transmission line and the loss in the dispersion compensating fiber A are offset by changing the gains of Er doped fiber amplifiers B, C. In this method, the gain of Er doped fiber amplifier B and C are off the designed value, thus the gain flatness is worsened. A variable attenuator may be used to offset the gap from the designed value of loss. In this method, although the gain flatness is not changed, an additional insertion loss worsens the noise property.

[0010] In the optical fiber communication system, although the Er doped optical fiber amplifiers have widely been used, the Er doped optical fiber amplifier also arises several problems. Further, the Raman amplifier also has problems that, since output of ordinary semiconductor laser is about 100 to 200 mW, gain obtained is relatively small, and that the gain is sensitive to change in power or wavelength of the pumping light. So that, when a semiconductor laser of Fabry-Perot type having relatively high output is used, noise due to gain fluctuation caused by its mode hopping becomes noticeable, and that, when the magnitude of the gain is adjusted, although drive current of the pumping laser must be changed, if the drive current is changed, since the fluctuation in the central wavelength is about 15 nm at the maximum, the wavelength dependency of gain will be greatly changed. Further, such shifting of the central wavelength is not preferable because such shifting causes change in joining loss of a WDM coupler for multiplexing the pumping light. In addition, the optical repeater also has a problem that the Er doped optical fiber amplifiers B, C must be re-designed for each system. Further, the deterioration of the noise property due to insertion of the dispersion compensating fiber is hard to be eliminated in the present systems.

[0011] In a Raman amplification method for amplifying optical signal by using a stimulated Raman scattering phenomenon, a communication optical fiber is used as an optical fiber acting as an amplifying medium, and, in a distributed amplifying system, a wavelength of pumping light and a wavelength of the optical signal are arranged in 1400nm-1600nm band having low loss and low wavelength dependency within a wide band of the communication optical fiber. In this case, regarding the loss of wavelength dependency of the optical fiber as the amplifying medium, a difference between maximum and minimum values is below about 0.2 dB/km in the above band, even in consideration of loss caused by hydroxyl ion (OH) having peak at 1380 nm. Further, even if each pumping powers in a multi-wavelength pumping system are not differentiated according to the wavelength dependence of the loss, the gain of the signals amplified by the pumping lights are substantially the same, there is no problem in practical use.

[0012] On the other hand, in a Raman amplifier operating as a discrete amplifier such as EDFA (rare earth doped fiber amplifier) it is necessary to pay attention to the package of the amplifier fiber, for a length of the fiber is about 10 km to about several tens of kilometers in order to obtain the required gain. Thus, it is convenient that the length of the fiber is minimized as less as possible. Although the length of the fiber can be shortened by using an optical fiber having great non-linearity, in the optical fiber having great non-linearity, it is difficult to reduce the transmission loss caused by OH generally having a band of 1380 nm, and Rayleigh scattering coefficient becomes great considerably in comparison with the communication fiber, with the result that the difference between the maximum and minimum values of fiber loss within the above-mentioned wavelength range becomes very great such as 1.5 to 10 dB/km. This means that, when the optical fiber having length of 3 km is used, the loss difference due to the wavelength of the pumping light becomes 4.5 dB to 30 dB. Thus, the wavelength division multiplexing signals cannot be uniformly amplified by using the pumping lights having the same intensities.

SUMMARY OF THE INVENTION

[0013] An object of the present invention is to provide a Raman amplification method capable of uniformly amplifying wavelength division multiplexing signals and suitable to be incorporated as a unit.

[0014] Another object of the present invention is to provide a Raman amplifier which can obtain required gain and

can reduce wavelength dependency of gain to the extent that usage of a gain flattening filter is not required and which can be used in a band of EDFA.


[0015] A further object of the present invention is to apply the Raman amplifier to an optical repeater constituted by an Er doped fiber amplifier (EDFA) and a dispersion compensating fiber (DCF) thereby to provide an optical repeater in which the EDFA is not required to be re-designed for each system and which can compensate dispersion in transmission line loss and/or DCF loss without deteriorating property of the optical repeater.

[0016] Further, by Raman-amplifying the DCF, the deterioration of noise property due to insertion of the DCF which could not be avoided in the conventional techniques is reduced.

[0017] An example of a Raman amplifier according to the present invention is shown in Figs. 1, 2 and 3. When a small-sized semiconductor laser 3 of Fabry-Perot type having relatively high output is used in a pumping means 1, relatively high gain can be obtained, and, since the semiconductor laser 3 of Fabry-Perot type has a wide line width of an oscillating wavelength, occurrence of stimulated Brillouin scattering due to the pumping light can be eliminated substantially. On the other hand, when a semiconductor laser of DFB type or DBR type, or a Master Oscillator Power Amplifier (MOPA) is used in the pumping means 1, since a fluctuation range of the oscillating wavelength is relatively small, a gain configuration is not changed by a driving condition. Further, occurrence of stimulated Brillouin scattering can be suppressed by effecting modulation.

[0018] Further, by selecting the interval between the central wavelengths of the pumping light to a value greater than 6 nm and smaller than 35 nm, the wavelength dependency of gain can be reduced to the extent that the gain flattening filter is not required. The central wavelength λ_c in this case is a value defined regarding the single pumping light and is represented by the following equation when it is assumed that a wavelength of an i -th longitudinal mode of laser oscillating is λ_i and light power included in that mode is P_i :

$$\lambda_c = \frac{\sum_i P_i \lambda_i}{\sum_i P_i}$$



[0019] The reasons why the interval between the central wavelengths of the pumping light is selected to a value greater than 6 nm is that the oscillating band width of the semiconductor laser 3 of Fabry-Perot type connected to an external resonator 5 having narrow reflection band width is about 3 nm as shown in Fig. 12, and that a WDM coupler 11 (Figs. 1, 2 and 3) for combining the pumping lights is permitted to have certain play or margin in wavelength interval between the pumping lights in order to improve wave combining efficiency. The WDM coupler 11 is designed so that lights having different wavelengths are received by different ports and the incident lights are joined at a single output port substantially without occurring of loss of lights. However, regarding light having intermediate wavelength between the designed wavelengths, the loss is increased even whichever port is used. For example, in a certain WDM coupler 11, a width of a wavelength band which increases the loss is 3 nm. Accordingly, in order that the band of the semiconductor laser 3 is not included within said band, as shown in Fig. 12, a value 6 nm obtained by adding 3 nm to the band width of the semiconductor laser 3 is proper for low limit of the interval between the central wavelengths of the pumping light. On the other hand, as shown in Fig. 13A, if the interval between the central wavelengths of the semiconductor laser 3 is greater than 35 nm, as shown in Fig. 13B, a gain valley is created at an intermediate portion of the Raman gain band obtained by the pumping lights having adjacent wavelengths, thereby worsening the gain flatness. The reason is that, regarding the Raman gain obtained by the single pumping light, at a position spaced apart from the gain peak wavelength by 15 nm to 20 nm, the gain is reduced to half. Accordingly, by selecting the interval of the central wavelengths of the pumping light to the value greater than 6 nm and smaller than 35 nm, the wavelength dependency of gain can be reduced to the extent that the gain flattening filter is not required.

[0020] According to a second aspect of the present invention, since a Raman amplifier has a control means 4 for monitoring input light or output light with respect to the Raman amplifier and for controlling pump powers of the pumping means 1 on the basis of a monitored result to maintain output light power of the Raman amplifier to a predetermined

value, given output can be obtained regardless of fluctuation of input signal power to the Raman amplifier and/or dispersion in loss of a Raman amplifier fiber.

[0021] According to a third aspect of the present invention, since a Raman amplifier has a controlling means 4 for flattening Raman gain, the gain can be flattened. Particularly, as shown in Fig. 16, by monitoring lights having wavelengths obtained by adding about 100 nm to the wavelengths of the pumping lights, respectively, and by controlling the powers of the pumping lights to order or align the monitored light powers, the gain can be flattened. Further, since a wavelength stabilizing fiber grating (external resonator 5) which will be described later can suppress the shift in the central wavelength due to change in drive current of a Fabry-Perot type semiconductor laser, it can also be used as a means for permitting control of the gain.

[0022] According to a fourth aspect of the present invention, since a Raman amplifier has a control means 4 for monitoring input signal power and output signal power and for controlling pumping light power to make a ratio between the input signal power and the output signal power constant thereby to maintain gain of the Raman amplifier to a predetermined value, given output can be obtained regardless of fluctuation of the input signal power to the Raman amplifier and/or dispersion in loss of a Raman amplifier fiber.

[0023] According to a fifth aspect of the present invention, in a Raman amplifier, since an optical fiber having non-linear index n_2 of refraction of $3.5E-20$ [m^2/W] or more is used as an optical fiber 2, adequate amplifying effect can be obtained, from the result of investigation.

[0024] According to a sixth aspect of the present invention, in a Raman amplifier, since the optical fiber 2 exists as a part of a transmission fiber for propagating the optical signal, the amplifier can be incorporated into the transmission optical fiber as it is.

[0025] According to a seventh aspect of the present invention, a Raman amplifier utilizes a part of a dispersion managed transmission line and can constitute an amplifier as it is as a amplifying medium.

[0026] According to an eighth aspect of the present invention, in a Raman amplifier, since the optical fiber 2 exists as an amplifier fiber provided independently from a transmission fiber for propagating the optical signal and inserted into the transmission fiber, an optical fiber suitable for Raman amplification can easily be used for the optical fiber 2 and the chromatic dispersion compensating fiber can easily be utilized, and a discrete amplifier can be constituted.

[0027] In an optical repeater according to the present invention, since loss of an optical fiber transmission line 8 is compensated by using the Raman amplifier, an optical repeater having the function of the Raman amplifier can be provided.

[0028] Among optical repeaters of the present invention, in a repeater in which rare earth doped fiber amplifier(s) 10 is (are) provided at preceding or following stage or at both stages of the Raman amplifier, since the loss of the optical fiber transmission line 8 is compensated by the Raman amplifier 9 and the rare earth doped fiber amplifier(s) 10, desired amplifying property suitable for various transmission systems can be obtained.

[0029] Among optical repeaters of the present invention, in accordance with an arrangement in which the Raman amplifier 9 and the rare earth doped fiber amplifier 10 are combined, a repeater adapted to various systems can be obtained. This fact will be explained hereinbelow as an example that DCF is used as the amplifier fiber of the Raman amplifier 9. Fig. 17 shows design parameters of a conventional optical repeater, and the gains G_1 , G_2 are varied for each system. Further, it is not inevitable that input of the repeater and loss of the DCF are fluctuated by scattering in repeater spacing and scattering in the DCF. Such fluctuation is directly associated with the fluctuation of the gain of the EDFA, which fluctuation of the gain leads to deterioration of flatness. Fig. 18 schematically shows a relationship between the flatness and the gain of the EDFA. Since the flatness is optimized by limiting the used band and the average gain, if the average gain is deviated from the optimum point, the wavelength dependency of gain is changed to worsen the flatness. In order to avoid the deterioration of the flatness, the gain of the EDFA must be kept constant. Conventionally, a variable attenuator has been used as a means for compensating the fluctuation in input level and loss of the DCF. Fig. 19A shows an example that an attenuating amount of the variable attenuator is adjusted in accordance with the fluctuation of the input level to control the input level to the DCF to be kept constant and Fig. 19B shows an example that an attenuating amount is adjusted in accordance with the fluctuation in loss of the DCF to control intermediate loss to be kept constant. In both examples, the gains of two amplifiers are constant. However, in these methods, since useless loss is added by the variable attenuator, there is an disadvantage in the viewpoint of noise property. In the present invention, by compensating the change in design parameters of the repeater by the Raman amplification of the DCF, the gain of the EDFA is kept constant, requirement that the EDFA be re-designed for each system is eliminated, and the scattering in repeater spacing and scattering in the DCF can be compensated without sacrificing the flatness and the noise property. Fig. 20 shows design values of the EDFA when the Raman amplification of the DCF is applied to the specification of the repeater of Fig. 17. By selecting the Raman gain of the DCF appropriately, the properties of the EDFA required for three specifications can be made common. Further, as shown in Figs. 21A and 21B, the fluctuation in input level and in loss of the DCF can be compensated by changing the Raman gain without changing the gain of the EDFA. In any cases, the Raman gain is adjusted so that the output level of the DCF becomes constant, while keeping the gain of the EDFA constant. Further, by compensating the loss of the DCF itself by the Raman amplification,

the deterioration of the noise property due to insertion of the DCF which could not be avoided in the conventional techniques can be reduced. Fig. 37 shows measured values of a deteriorating amount of the noise figure when the DCF is inserted and of a deteriorating amount of the noise figure when the Raman amplifier using the same DCF is inserted.

[0030] In the optical repeater according to the present invention, when a Raman amplifier using a pumping light source in which wavelengths are not combined is provided, although an operating wavelength range is narrower, a construction can be simplified and the same property as the aforementioned optical repeaters can be obtained, except for the band width, in comparison with an optical repeater having a Raman amplifier pumped by a plurality of wavelengths. Figs. 38 and 39 show measured examples of the optical repeater using the Raman amplifier pumped by the pumping light source in which wavelengths are not combined and of the optical repeater using the Raman amplifier pumped by the plurality of wavelengths.

[0031] In the Raman amplifier according to the present invention, when a difference between maximum and minimum values of the central wavelength of the pumping light is within 100 nm, overlapping between the pumping light and the optical signal can be prevented to prevent wave form distortion of the optical signal. If the wavelength of the pumping light is similar to the wavelength of the optical signal, since the wave form of the optical signal may be deteriorated, the wavelength of the pumping light and the wavelength of the optical signal must be selected so that they are not overlapped. However, in a case where the pumping light has a band of 1.4 μm , when the difference between the maximum and minimum values of the central wavelength of the pumping light is smaller than 100 nm, as shown in Fig. 14, since the difference between the central wavelength of the gain caused by one pumping light and the wavelength of such pumping light is about 100 nm, the overlapping between the wavelength of the pumping light and the wavelength of the optical signal can be prevented.

[0032] In the Raman amplifier according to the present invention, when the pumping lights having adjacent wavelengths are propagated through the optical fiber 2 toward two different directions so that the optical signal is pumped bidirectionally, the wavelength property required in the WDM coupler 11 shown in Fig. 1 and Figs. 2 and 3 can be softened. The reason is that, as shown in Fig. 15, in all of pumping lights from both directions, although the central wavelengths become $\lambda_1, \lambda_2, \lambda_3, \lambda_4$ and the interval is greater than 6 nm and smaller than 35 nm, when considering the pumping lights from only one direction, the central wavelengths become λ_1 and λ_3 or λ_2 and λ_4 and the wavelength interval increased to twice, with the result that the property required in the WDM coupler 11 can have margin or play.

[0033] In the Raman amplifier according to the present invention, when the wavelength stabilizing external resonator 5 such as fiber grating is provided at the output side of the semiconductor laser 3 of Fabry-Perot type, noise due to fluctuation of caused by mode hopping of the semiconductor laser 3 of Fabry-Perot type can be suppressed. In consideration of one pumping light source, it makes the bandwidth narrower to connect the wavelength stabilizing external resonator 5 to the semiconductor laser 3. Since it also results the smaller wavelength interval in case of combining pumping light sources by the WDM coupler 11 (Figs. 1, 2 and 3), pumping light having higher output and wider band can be generated.

[0034] In the Raman amplifier according to the present invention, when the pumping light of the semiconductor laser 3 is used to be polarization-combined for each wavelength, not only polarization dependency of gain can be eliminated but also the pump power launched into the optical fiber 2 can be increased. In the Raman amplification, only the components matched with the polarization of the pumping light can be given the gain. When the pumping light is linear-polarized and the amplifier fiber is not a polarization maintaining fiber, the gain is changed due to fluctuation of relative state of polarization of the signal and the pumping light. Therefore, the polarization dependence of gain can be eliminated by combining two linear-polarized pumping lights so that the polarization planes are perpendicular to each other. Further, it increases the pumping light power launched into the fiber.

[0035] In the Raman amplifier according to the present invention, in the case where a wavelength combiner of planar lightwave circuit based on a Mach-Zehnder interferometer is used as a means for wave-combining MOPA or a semiconductor laser of Fabry-Perot type, DFB type or DBR type having a plurality of wavelengths, even when the number of the wavelengths to be combined is large, the wave-combination can be achieved with very low loss, and pumping light having high output can be obtained.

[0036] In the Raman amplifier according to the present invention, as shown in Fig. 6, when a polarization plane rotating means 7 for rotating the polarization plane by 90 degrees is provided so that the optical fiber 2 simultaneously includes the plurality of pumping lights generated by the pumping means 1 and the pumping lights having a orthogonal state of polarization to the pumping lights generated by the pumping means 1, in principle, given gain can always be obtained regardless of the state of polarization of the optical signal, with the result that the band of the Raman gain can be widened.

[0037] In the optical repeater according to the present invention, when the Raman amplification is utilized by coupling residual pumping light of the Raman amplifier to the optical fiber transmission line 8, a part of loss of the optical fiber transmission line 8 can be compensated.

[0038] In the optical repeater according to the present invention, when the residual pumping light of the Raman amplifier is utilized as pumping light for the rare earth doped fiber amplifier 10, the number of the semiconductor lasers

to be used can be reduced.

[0039] In the optical repeater according to the present invention, when a dispersion compensating fiber is used as the optical fiber 2 of the Raman amplifier 9, the chromatic dispersion of the optical fiber transmission line 8 can be compensated by the Raman amplifier 9, and a part or all of the losses in the optical fiber transmission line 8 and the amplifier fiber 2 can be compensated.

[0040] According to a twenty-ninth aspect of the present invention, in a Raman amplification method by stimulated Raman scattering in an optical fiber through which two or more pumping lights having different central wavelengths and said optical signals are propagated, the pumping power launched into said optical fiber increases as the central wavelengths of said pumping lights is shorter.

[0041] According to a thirtieth aspect of the present invention, in a Raman amplification method by stimulated Raman scattering in an optical fiber through which two or more pumping lights having different central wavelengths and said optical signals are propagated, total pumping power on the shorter wavelength side with respect to the center between the shortest and longest central wavelengths among said two or more pumping lights is greater than on the longer side.

[0042] According to a thirty-first aspect of the present invention, in a Raman amplification method by stimulated Raman scattering in an optical fiber through which three or more pumping lights having different central wavelengths and said optical signals are propagated, the number of the pumping light sources on the shorter wavelength side with respect to the center between the shortest and longest central wavelengths among said three or more pumping lights is greater than on the longer side, and the total pumping power on the shorter wavelength side is greater than on the longer side.

BRIEF DESCRIPTION OF THE DRAWINGS

[0043]

Fig. 1 is a diagram showing a first embodiment of a Raman amplifier according to the present invention;

Fig. 2 is a diagram showing a second embodiment of a Raman amplifier according to the present invention;

Fig. 3 is a diagram showing a third embodiment of a Raman amplifier according to the present invention;

Fig. 4 is a diagram showing a first example of a controlling means in the Raman amplifier according to the present invention;

Fig. 5 is a diagram showing a second example of a controlling means in the Raman amplifier according to the present invention;

Figs. 6A and 6B are diagrams showing different examples of a polarization plane rotating means in the Raman amplifier according to the present invention;

Fig. 7 is a diagram showing a first embodiment of an optical repeater according to the present invention;

Fig. 8 is a diagram showing a second embodiment of an optical repeater according to the present invention;

Fig. 9 is a diagram showing a third embodiment of an optical repeater according to the present invention;

Fig. 10 is a diagram showing a fourth embodiment of an optical repeater according to the present invention;

Fig. 11 is a diagram showing a fifth embodiment of an optical repeater according to the present invention;

Fig. 12 is an illustration of why a wavelength interval of pumping light is selected to be greater than 6 nm;

Figs. 13A and 13B are illustrations of why a wavelength interval of pumping light is selected to be smaller than 35 nm;

Fig. 14 is an illustration of why a difference between a longest wavelength and a shortest wavelength is selected to be smaller than 100 nm;

Fig. 15 is an illustration of an example of wavelength arrangement of pumping lights in bi-directional pumping;

Fig. 16 is an illustration of how a condition that a gain over a specified band is flattened by controlling pumping light power;

Figs. 17A and 17B are illustrations of properties associated with designing of the optical repeater;

Fig. 18 is an illustration of a relationship between fluctuation in gain of EDFA and deterioration of flatness;

Fig. 19A is an illustration of how a condition that fluctuation in input level due to a variable attenuator is compensated, and Fig. 19B is an explanatory view showing a condition that fluctuation in loss of DCF due to a variable attenuator is compensated;

Figs. 20A and 20B are illustrations of properties associated with designing of the optical repeater utilizing a Raman amplification in DCF;

Fig. 21A is an illustration of how a condition that fluctuation in input level due to the Raman amplification is compensated, and Fig. 21B is an explanatory view showing a condition that fluctuation in loss of DCF due to the Raman amplification is compensated;

Fig. 22 is an illustration of different examples of output spectrum in the Raman amplifier;

Fig. 23 is an illustration of wavelength dependency of gain due to EDFA;

Fig. 24 is an illustration of fluctuation in gain due to EDFA;

Fig. 25 is an illustration of wavelength dependency of gain due to Raman amplification;

Fig. 26 is a diagram showing a control method for controlling output light power by monitoring input light;

Fig. 27 is a diagram showing a control method for controlling output light power by monitoring output light;

Fig. 28 is a diagram showing a control method for controlling output light power by monitoring input light and output light;

Fig. 29 is a diagram showing a first example of a method for obtaining Raman gain by coupling residual pumping light of the Raman amplifier to an optical fiber transmission line;

Fig. 30 is a diagram showing a second example of a method for obtaining Raman gain by coupling residual pumping light of the Raman amplifier to an optical fiber transmission line;

Fig. 31 is a diagram showing a third example of a method for obtaining Raman gain by coupling residual pumping light of the Raman amplifier to an optical fiber transmission line;

Fig. 32 is a diagram showing a fourth example of a method for obtaining Raman gain by coupling residual pumping light of the Raman amplifier to an optical fiber transmission line;

Fig. 33 is a diagram showing a first example of a method for utilizing the residual pumping light of the Raman amplifier as pumping light of EDFA;

Fig. 34 is a diagram showing a second example of a method for utilizing the residual pumping light of the Raman amplifier as pumping light of EDFA;

Fig. 35 is a diagram showing a third example of a method for utilizing the residual pumping light of the Raman amplifier as pumping light of EDFA;

Fig. 36 is a diagram showing a fourth example of a method for utilizing the residual pumping light of the Raman amplifier as pumping light of EDFA;

Fig. 37 is an illustration of deterioration of noise figure due to insertion of a dispersion compensating fiber;

Fig. 38 is an illustration of the number of pumping wavelengths of the Raman amplifier and property of the repeater;

Fig. 39 is an illustration of the number of pumping wavelengths of the Raman amplifier and property of the repeater;

Fig. 40 is a diagram of an optical repeater in which a plurality of Raman amplifiers are connected in a multi-stage fashion;

Fig. 41 is a diagram showing an example of a pumping means having a single pumping light source;

Fig. 42 is a diagram showing another example of a pumping means having a single pumping light source;

Fig. 43 is a diagram showing an example of a pumping means having two pumping light sources;

Fig. 44 is a diagram showing another example of a pumping means having two pumping light sources;

Fig. 45 is a diagram of a Raman amplifier in which a dispersion compensating fiber is used as an amplifier fiber;

Fig. 46 is a diagram showing an example of a conventional optical repeater;

Fig. 47 is an illustration of signal level diagram in the optical repeater of Fig. 46;

Fig. 48 is a diagram showing a case where SMF and a fiber having dispersion smaller than $-20/\text{ps}/\text{nm}/\text{km}$ are used as the amplifier fiber;

Fig. 49 is an illustration of an example of an arrangement for carrying out a Raman amplification method according to the present invention;

Fig. 50 is an explanatory view showing an pumping light source of Fig. 49;

Fig. 51 is a view showing gain profile of a optical signal Raman-amplified by the Raman amplifying method according to the present invention;

Fig. 52 is a view showing gain profile of a optical signal Raman-amplified by a conventional method;

Fig. 53 is an explanatory view showing another example of an arrangement for carrying out a Raman amplification method according to the present invention;

BEST MODE FOR CARRYING OUT THE INVENTION

(First embodiment of Raman amplifier)

[0044] Fig. 1 shows a first embodiment of a Raman amplifier according to the present invention. The Raman amplifier comprises a signal input fiber 12, an amplifier fiber (optical fiber) 2, a WDM coupler 13, a pumping means 1, a tap coupler for monitoring 14, a monitor signal detecting and LD control signal generating circuit 15, a signal output fiber 16, and a polarization independent isolator 25. The tap coupler for monitoring 14 and the monitor signal detecting and LD control signal generating circuit 15 constitute a controlling means 4.

[0045] The pumping means 1 includes semiconductor lasers 3 ($3_1, 3_2, 3_3, 3_4$) of Fabry-Perot type, wavelength stabilizing fiber ratings (external resonators) 5 ($5_1, 5_2, 5_3, 5_4$), polarization coupler (polarization beam combiner) 6 ($6_1, 6_1$), and a WDM coupler 11. Oscillating wavelengths of the semiconductor lasers $3_1, 3_2$ and permeation wavelengths of the

fiber gratings 5₁, 5₂ are the same wavelength λ_1 , and central wavelengths of the semiconductor lasers 3₃, 3₄ and permeation wavelengths of the fiber gratings 5₃, 5₄ are the same wavelength λ_2 , and the oscillating wavelengths of the semiconductor lasers 3₁, 3₂, 3₃, 3₄ can be subjected to the action of the wavelength stabilizing fiber gratings 5₁, 5₂, 5₃, 5₄ so that the central wavelengths are stabilized to λ_1 , λ_2 . Further, a wavelength interval between the wavelength λ_1 and the wavelength λ_2 is selected to be greater than 6 nm and smaller than 35 nm.

[0046] Pumping lights generated by the semiconductor lasers 3₁, 3₂, 3₃, 3₄ are polarization-combined by the polarization coupler 6 for each wavelength λ_1 , λ_2 , and output lights from the polarization coupler 6 are combined by the WDM coupler 11 to obtain output light of the pumping means 1. Polarization maintaining fibers 17 are connected between the semiconductor lasers 3 and the polarization coupler 6 to obtain two pumping lights having different polarization planes. The output light of the pumping means 1 is coupled to the amplifier fiber 2 via the WDM coupler 13; on the other hand, an optical signal (wavelength division multiplexing signal) is incident on the amplifier fiber 2 from the optical signal input fiber 12 and then is combined with the pumping light of the pumping means 1 in the amplifier fiber 2 to be Raman-amplified, and the Raman-amplified light is passed through the WDM coupler 13 and is sent to the monitor light branching coupler 14, where a part of the light is branched as a monitor signal, and the other is outputted to the optical signal output fiber 16. The monitor signal is monitored in the monitor signal detecting and LD control signal generating circuit 15, and the circuit 15 generate a signal for controlling drive currents for the semiconductor lasers 3 so that gain deviation in the signal wavelength band becomes small.

[0047] The amplifier fiber 2 may be a special fiber suitable for Raman amplification (for example, a fiber having non-linear index of refraction n_2 of 3.5 E-20 [m²/W] or more) or may be an extension of the signal input fiber 12 by which the optical signal is received. Further, as shown in Fig. 48, RDF (reverse dispersion fiber) having dispersion of less than -20 ps/nm per 1 km may be connected to SMF so that the amplifier fiber can also act as a transmission line. (Generally, since RDF has dispersion of less than -20 ps/nm, RDF having a length substantially the same as or greater, by twice, than a length of SMF may be used.) In such a case, preferably, it is designed so that the Raman amplifying pumping light is propagated from the RDF toward the SMF. In the Raman amplifier, the amplifier fiber 2 may be connected to and inserted into a transmission fiber (not shown) to which the optical signal is transmitted, and the amplifier fiber 2, pumping means 1, WDM coupler 13, monitor light branching coupler 14, and monitor signal detecting and LD control signal generating circuit 15 may be incorporated to constitute a concentrated Raman amplifier.

[0048] Fig. 22 shows the output spectrum of the Raman amplifier of Fig. 1. In this experiment, the wavelength of 1435 nm and 1465 nm were used as the pumping wavelengths λ_1 and λ_2 in Fig. 1. The power of the input signals is -20 dBm/ch, and the wavelengths are arranged at an even space between 1540 nm and 1560 nm. The amplifier fiber 2 was a dispersion compensating fiber having a length of about 6 km, and powers of the pumping lights were adjusted to compensate the loss of the dispersion compensating fiber while keeping deviation between channels within 0.5 dB.

(Second embodiment of Raman amplifier)

[0049] Fig. 2 shows a second embodiment of a Raman amplifier according to the present invention, in which the pumping light from the pumping means 1 is propagated toward the same direction of the optical signal in the amplifier fiber 2. More specifically, the WDM coupler 13 is provided at a input end of the amplifier fiber 2, and the pumping light from the pumping means 1 is transmitted, through the WDM coupler 13, from the input end to output end of the amplifier fiber 2. In this arrangement, since amplification is effected before attenuation of signal, the noise property of the optical signal is superior to that in the first embodiment. Further, it was found that the gain is smaller in comparison with the first embodiment.

(Third embodiment of Raman amplifier)

[0050] Fig. 3 shows a third embodiment of a Raman amplifier according to the present invention, in which pumping lights from an pumping means 1 are propagated in two directions through the amplifier fiber 2. More specifically, WDM couplers 13 are provided at input and output ends of the amplifier fiber 2, respectively, and the pumping lights from two groups of the pumping means 1 are coupled to the amplifier fiber 2 through the respective WDM couplers 13 so that the pumping light launched into the input side WDM coupler 13 is propagated toward the output end of the amplifier fiber 2 and the pumping light launched into the output side WDM coupler 13 is propagated toward the input end of the amplifier fiber 2.

[0051] Central wavelengths of semiconductor lasers 3₁, 3₂ included in the first group A of the pumping means 1 and central wavelengths of semiconductor lasers 3₅, 3₆ included in the second group B are the same, and central wavelengths of semiconductor lasers 3₃, 3₄ included in the first group A and central wavelengths of semiconductor lasers 3₇, 3₈ included in the second group B are the same. Further, fiber gratings 5₁ to 5₈ are matched with the central wavelength of the semiconductor lasers 3 to which the fiber gratings are connected, respectively.

(Fourth embodiment of Raman amplifier)

[0052] In the embodiment shown in Fig. 3, when it is assumed that the central wavelengths of the semiconductor lasers 3_1 , 3_2 included in the first group A are λ_1 , central wavelengths of the semiconductor lasers 3_3 , 3_4 included in the first group A are λ_3 , central wavelengths of the semiconductor lasers 3_5 , 3_6 included in the second group B are λ_2 , and central wavelengths of the semiconductor lasers 3_7 , 3_8 included in the second group B are λ_4 , the wavelengths λ_1 , λ_2 , λ_3 , λ_4 may be adjacent wavelengths. Also in this case, the interval between the central wavelengths is greater than 6 nm and smaller than 35, and the difference between the maximum central wavelength λ_4 and the minimum central wavelength λ_1 is smaller than 100 nm. With this arrangement, the wavelength interval of the pumping lights combined in the same group can have play or margin and performance required for the WDM couplers 13 can be loosened.

(Fifth embodiment of Raman amplifier)

[0053] Fig. 40 shows a fifth embodiment of a Raman amplifier according to the present invention. In this embodiment, appropriate Raman amplifiers are selected among the Raman amplifiers 9 described in the above-mentioned embodiments and the selected Raman amplifiers are connected together in a multi-stage fashion. By properly selecting the Raman amplifiers 9 having different characteristics in accordance with the desired amplifying property and noise property, a property which could not be achieved by a single Raman amplifier can be obtained.

[0054] In the above-mentioned embodiments, the output light power controlling means 4 may be designed as shown in Fig. 4 or Fig. 5. In an arrangement shown in Fig. 4, a monitor signal detecting and LD control signal generating circuit 15 comprising a wavelength demultiplexer 18, optical/electrical converting means 19 such as photo-diodes and an LD control circuit 20 is connected to a monitor light branching coupler 14 as shown in Fig. 1, 2, or 3. The wavelength demultiplexer 18 serves to demultiplex the output light branched by the monitor light branching coupler 14 into a plurality of wavelength lights. In this case, lights near the maximum amplification wavelengths (each of which is a wavelength obtained by adding 100 nm to the pumping light wavelength) of the respective pumping lights are demultiplexed (more specifically, when the pumping wavelengths are 1430 nm and 1460 nm, wavelength lights near 1530 nm and 1560 nm are demultiplexed). Each of the optical/electrical converting means 19 serves to convert the received wavelength light into an electrical signal, so that output voltage is varied with magnitude of the light receiving level. The LD control circuit 20 serves to change the drive currents for the semiconductor lasers 3 in accordance with the output voltages from the optical/electrical converting means 19, and, by calculating and processing the output voltage from the optical/electrical converting means 19, the semiconductor lasers 3 are controlled so that light powers of the wavelength lights are ordered or aligned. That is to say, the output light power controlling means 4 acts to eliminate the wavelength dependency of the Raman gain thereby to flatten the gain.

[0055] In an arrangement shown in Fig. 5, a monitor signal detecting and LD control signal generating circuit 15 comprising a power splitter 21, band pass filters 22, optical/electrical converting means 19 such as photo-diodes and an LD control circuit 20 is connected to a monitor light branching coupler 14. The power splitter 21 serves to branch the output light branched by the monitor light branching coupler 14 into lights having the same number as the pumping lights. The band pass filters 22 have different permeable central wavelengths, and, in this case, permit to pass lights near the maximum amplification wavelengths (each of which is a wavelength obtained by adding 100 nm to the pumping light wavelength) of the respective pumping lights (more specifically, when the pumping wavelengths are 1430 nm and 1460 nm, pass of wavelength lights near 1530 nm and 1560 nm are permitted). Each of the optical/electrical converting means 19 serves to convert the received wavelength light into an electrical signal, so that output voltage is varied with magnitude of the light receiving level. The LD control circuit 20 serves to change the drive currents for the semiconductor lasers 3 in accordance with the output voltages from the optical/electrical converting means 19, and, by calculating and processing the output voltage from the optical/electrical converting means 19, the semiconductor lasers 3 are controlled so that light powers of the wavelength lights are ordered or aligned. That is to say, the output light power controlling means 4 acts to eliminate the wavelength dependency of the Raman gain thereby to flatten the gain. Although Figs. 4 and 5 show arrangements for controlling the pumping means 1 by monitoring the output light as shown in Fig. 27, as shown in Fig. 26, an arrangement for controlling the pumping means 1 by monitoring the input light can be utilized, or, as shown in Fig. 28, an arrangement for controlling the pumping means 1 by monitoring both the input light and the output light can be utilized.

[0056] In the Raman amplifiers having the above-mentioned constructions, in place of the fact the pumping lights are combined by the polarization wave composing coupler 6, as shown in Figs. 6A and 6B, a polarization plane rotating means 7 for rotating polarization plane of the pumping light by 90 degrees may be provided, so that the plural pumping lights generated by the pumping means 1 and pumping lights having polarization planes perpendicular to those of the former pumping lights are simultaneously pumped in the amplifier fiber 2. Fig. 6A shows an arrangement in which a Faraday rotator 3_1 and a total reflecting mirror 3_2 are provided at an end of the amplifier fiber 2 so that the polarization plane of the pumping light propagated to the amplifier fiber 2 is rotated by 90 degrees to be returned to the amplifier

fiber 2 again, in Fig. 6, a means for picking up the optical signal propagated to and Raman-amplified in the amplifier fiber 2 from the fiber 2 is not shown. Fig. 6B shows an arrangement in which a PBS 33 and a polarization maintaining fiber 34 are provided at an end of the amplifier fiber 2 so that the polarization plane of the pumping light outputted from the end of the amplifier fiber 2 is rotated by 90 degrees by the polarization maintaining fiber 34 connected to twist its main axis by 90 degrees, to be inputted to the end of the amplifier fiber 2 again through the PBS 33.

(First embodiment of optical repeater)

[0057] Fig. 7 shows a first embodiment of an optical repeater constructed by using the Raman amplifier according to the present invention. In this example, the optical repeater is inserted into an optical fiber transmission line 8 to compensate loss in the optical fiber transmission line 8. In this optical repeater, a rare earth doped fiber amplifier (referred to as "EDFA" hereinafter) 10 is connected to a rear stage of the Raman amplifier 9 as shown in Fig. 1, 2 or 3 so that the optical signal transmitted to the optical fiber transmission line 8 is inputted to the Raman amplifier 9 to be amplified and then is inputted to the EDFA 10 to be further amplified and then is outputted to the optical fiber transmission line 8. The gain of the repeater may be adjusted by the Raman amplifier 9 or by the EDFA 10 or by both amplifiers so long as the loss of the optical fiber transmission line 8 can be compensated in total. Further, by properly combining a difference between the wavelength dependency of gain of the EDFA 10 and the wavelength dependency of the Raman amplifier 9, the wavelength dependency of gain of the EDFA 10 can be reduced by the wavelength dependency of the Raman amplifier 9.

(Second embodiment of optical repeater)

[0058] Fig. 8 shows a second embodiment of an optical repeater constructed by using the Raman amplifier according to the present invention. According to this embodiment, in the optical repeater shown in Fig. 7, an additional EDFA 10 is also provided at a front stage of the Raman amplifier 9. Incidentally, the EDFA 10 may be provided only at the front stage of the Raman amplifier 9.

(Third embodiment of optical repeater)

[0059] Fig. 9 shows a third embodiment of an optical repeater constructed by using the Raman amplifier according to the present invention. According to this embodiment, there is provided a Raman amplifier 9 in which a dispersion compensating fiber (DCF) is used as the amplifier fiber 2 between two EDFAs 10. Between the Raman amplifier 9 and the EDFA 10 at the rear stage thereof, there are provided a branching coupler 23 for branching the output light from the Raman amplifier 9, and a monitor signal detecting and LD control signal generating circuit 24 for monitoring the branched light and for controlling the gain of the Raman amplifier 9. The monitor signal detecting and LD control signal generating circuit 24 is a control circuit capable of keeping the output power of the Raman amplifier 9 to a predetermined value. Incidentally, when the Raman amplifier 9 itself has the controlling means 4 as shown in Fig. 4 or Fig. 5, the power of the output light is controlled to become the predetermined value, and, at the same time, the power of the pumping light is controlled so that level deviation between plural output signals become small.

[0060] In the optical repeater shown in Fig. 9, the output light level of the Raman amplifier 9, i.e., input level to the second EDFA 10 is always kept constant without being influenced by the loss of the DCF and the output level of the first EDFA 10. This ensures that, when the output of the repeater is defined, the gain of the second EDFA 10 is kept constant. In this way, deterioration of gain flatness of the second EDFA 10 due to fluctuation in loss of the DCF is avoided. Further, when the first EDFA 10 is controlled so that the gain becomes constant, the fluctuation of input to the repeater is compensated by the varying of gain of the Raman amplifier 9. Namely, the adjustment is effected only on the basis of the gain of the Raman amplifier 9, with the result that the deterioration of gain flatness due to fluctuation in gain of the EDFA 10 can be avoided completely.

(Fourth embodiment of optical repeater)

[0061] Fig. 10 shows an example that, in the embodiment shown in Fig. 9, a control means for adjusting the gain of the Raman amplifier 9 by monitoring the light level is also provided between the first EDFA 10 and the Raman amplifier 9. By using such control means, the pumping light can be controlled to keep the difference between the input and output levels of the Raman amplifier 9 constant, with the result that only the dispersion of the loss of the DCF can be compensated.

(Fifth embodiment of optical repeater)

[0062] Fig. 11 shows an example that, in the above-mentioned embodiment, the gain flattening monitor mechanism is shifted to the output end of the repeater and is used as a monitor for flattening the gain of the entire repeater. In this case, the first EDFA 10 and the second EDFA 10 may perform the gain constant control or the output constant control. The powers of the pumping lights are independently controlled to reduce the level deviation between the output signals at the output of the repeater.

(Sixth embodiment of optical repeater)

[0063] In an optical repeater according to a sixth embodiment of the present invention, a dispersion compensating fiber is used as the amplifier fiber 2 of the Raman amplifier shown in Fig. 1, 2 or 3 to compensate dispersion of wavelength of the optical fiber transmission line 8, so that the losses in the optical fiber transmission line 8 and the amplifier fiber 2 are compensated partially or totally.

(Seventh embodiment of optical repeater)

[0064] In the above-mentioned embodiment of the optical repeater, a Raman amplifier 9 using an pumping means 1 shown in Fig. 41, 42, 43 or 44 may be constituted.

(Eighth embodiment of optical repeater)

[0065] As shown in Figs. 29 to 32, WDM couplers 13 are inserted on the way of the amplifier fiber 2 of the Raman amplifier 9 so that residual pumping light from the pumping means 1 propagated to the amplifier fiber 2 is inputted to the optical fiber transmission line 8 through a WDM coupler 27 provided in the optical fiber transmission line 8 at the input or output side of the Raman amplifier 9, thereby also generating Raman gain in the optical fiber transmission line 8. Incidentally, in Figs. 29 to 32, the reference numeral 26 denotes an isolator.

(Ninth embodiment of optical repeater)

[0066] As shown in Figs. 33 to 36, when the optical repeater comprises the Raman amplifier 9 and the EDFA 10, WDM couplers 13 are inserted on the way of the amplifier fiber 2 of the Raman amplifier 9 so that residual pumping light from the pumping means 1 propagated to the amplifier fiber 2 is inputted to the EDFA 10 to be used as pumping light/auxiliary pumping light for the EDFA 10. Incidentally, in Figs. 33 to 36, the reference numeral 26 denotes an isolator.

(First embodiment of Raman amplifying method)

[0067] An embodiment of a Raman amplifying method according to the present invention will now be fully explained with reference to Figs. 49 to 52. In this embodiment, a dispersion compensating fiber (DCF) having high non-linearity is used in a Raman amplifying medium 50 shown in Fig. 49 and pumping light generated from an pumping light source 51 is inputted and transmitted to the Raman amplifying medium through a wave combiner 52. In this case, as shown in Fig. 50, as the pumping light source 50, a 4ch-WDMLD unit comprising four pumping light sources (semiconductor lasers), fiber Bragg gratings (FBG), polarization beam combiner (PBC) and a WDM is used. The semiconductor lasers shown in Fig. 50 generate pumping lights having different central wavelengths (more specifically, generate pumping lights having central wavelengths of 1435 nm, 1450 nm, 1465 nm and 1480 nm, respectively). These pumping lights give Raman gain to an optical signal transmitted from the DCF, thereby amplifying the optical signal. In this case, each of the pumping lights has gain peak at frequency shorter than its frequency by about 13 THz (i.e., wavelength greater by about 100 nm).

[0068] When the optical signal having wavelength of 1500 nm to 1600 nm is propagated to the DCF having a length of 6 km from one end thereof and the pumping lights having wavelengths of 1400 nm, 1420 nm, 1440 nm, 1460 nm, and 1480 nm are inputted to the DCF thereby to Raman-amplify the optical signal, the input optical signal and an output optical signal outputted from the other end of the DCF (Raman-amplified optical signal) were checked to evaluate total loss of the wavelength and DCF. The following Table 1 shows a relationship between the wavelength and DCF total loss. From this, it is apparent that there is wavelength dependency:

Table 1

wavelength (nm)	unit loss (dB/km)	total loss (dB)
1400	6.76	40.56
1420	3.28	19.68
1440	1.74	10.44
1460	1.16	6.96
1480	0.85	5.10
1500	0.69	4.14
1520	0.62	3.72
1540	0.57	3.42
1560	0.55	3.30
1580	0.54	3.24
1600	0.59	3.54

[0069] Here, when it is considered that effect total loss is given by adding the loss of the semiconductor laser to the loss of the optical signal amplified by the semiconductor laser at the side of the longer wavelength greater by about 100 nm, a relationship between the wavelength and the effect total loss becomes as shown in the following Table 2:

Table 2

wavelength (nm)	effect total loss (dB)	
1400	40.56+4.14	44.7
1420	19.68+3.72	23.4
1440	10.44+3.42	13.86
1460	6.96+3.30	10.26
1480	5.10+3.24	8.34

[0070] Since there is substantially no wavelength dependency of the Raman amplification itself, when it is regarded that amplifying efficiency for each wavelength is influenced by the effect total loss, by adding the effect total loss to the outputs of the semiconductor lasers required for desired amplifying properties, the wavelengths can be Raman-amplified substantially uniformly, and the wavelength dependency of the gain can be eliminated. Thus, in this embodiment, the shorter the central wavelength of the pumping light the higher the light power.

(Second embodiment of Raman amplifying method)

[0071] In a Raman amplifying method according to a second embodiment of the present invention, in order to Raman-amplify substantially uniformly the optical signals having wavelengths of 1500 nm to 1600 nm transmitted by the DCF, among two or more pumping lights incident on the DCF, light powers of pumping lights having wavelengths smaller than center (middle) between the shortest central wavelength and the longest central wavelength are increased. More specifically, central wavelengths of the pumping lights generated by the pumping light source 51 shown in Fig. 50 and incident on the DCF are selected to 1435 nm, 1450 nm, 1465 nm and 1480 nm and the light powers thereof are selected as follows. That is to say, the light powers of the pumping lights having the wavelengths of 1435 nm and 1450 nm which are smaller than the center (1457 nm) between the shortest central wavelength (1435 nm) and the longest central wavelength (1480 nm) among four pumping lights incident on the DCF are increased, as follows:

Light power of 1435 nm	563 mW
Light power of 1450 nm	311 mW
Light power of 1465 nm	122 mW
Light power of 1480 nm	244 mW

[0072] As a result, the gain profile of the optical signal having wavelength of 1500 nm to 1600 nm (after Raman-amplified) transmitted by the DCF provides gain of about 11 dB from 1540 nm to 1590 nm, with the result that the flatness becomes 1 dB, as shown in Fig. 51. That is to say, the wavelength lights transmitted by the DCF can be Raman-amplified substantially uniformly.

[0073] Incidentally, when the central wavelengths of the pumping lights generated by the pumping light source 51 and incident on the DCF are selected to 1435 nm, 1450 nm, 1465 nm and 1480 nm and the light powers thereof are selected to 563 mW uniformly, the gain profile of the optical signal having wavelength of 1500 nm to 1600 nm (after Raman-amplified) transmitted by the DCF becomes as shown in Fig. 52. That is to say, although gain of about 24 dB can be obtained near the wavelength of 1580 nm, wide band gain flatness cannot be achieved (loss spectrum of the fiber is turned over).

(Third embodiment of Raman amplifying method)

[0074] Fig. 53 shows a third embodiment of a Raman amplifying method according to the present invention. In the Raman amplifying method shown in Fig. 53, pumping lights are combined by a wave combiner utilizing a principle of a Mach-Zehnder interferometer. The wavelengths of the pumping lights which can be combined becomes equidistant. In this embodiment, among wavelengths which can be combined, several wavelengths are not used, and the wavelength number at the short wavelength side of the pumping light band is greater than the wavelength number at the long wavelength side. In this arrangement, when the power of all of the pumping lights having various wavelengths are the same, the total power of the pumping lights at the short wavelength side becomes greater than the total power of the pumping lights at the long wavelength side. This provides substantially the same effect, similar to the second embodiment, as the effect obtained by setting the power at the short wavelength side to be greater than the power at the long wavelength side under the condition that the pumping lights are arranged equidistantly. Accordingly, by setting as shown in Fig. 53, the gain profile can be flattened without creating great difference between the powers of the pumping lights. This means that the total power of the pumping lights in which gain profile in a predetermined band can be flattened can be increased with determining the upper limit of the output power from one pumping light and therefore that the gain of the amplifier can be increased.

Industrial Availability

[0075] In the Raman amplifier according to the present invention, by selecting the wavelengths of the pumping light sources so that the interval between the central wavelengths becomes greater than 6 nm and smaller than 35 nm and the difference between the maximum central wavelength and the minimum central wavelength becomes within 100 nm, there can be provided an optical amplifier in which the wavelength dependency of gain is reduced to the extent that the gain flattening filter is not required and in which, if the gain is changed, the flatness can be maintained. Further, this amplifier can be applied to an optical repeater for compensating loss of a transmission line and wavelength dispersion. In a repeater constituted by the combination of the amplifier and EDFA, fluctuation of the EDFA due to fluctuation of input of the repeater and/or fluctuation in loss of DCF can be suppressed to avoid deterioration of gain flatness and the repeater can be applied to various systems.

[0076] In the Raman amplifying method according to the present invention, since the shorter center wavelength of the pumping light among two or more pumping lights incident on the DCF the greater the power, or, since the power of the pumping light at the short wavelength side with respect to the center between the shortest central wavelength and the longest central wavelength among two or more pumping lights incident on the DCF is increased, in any cases, even when an optical fiber having high non-linearity is used, wavelength multiplexing lights of about 1500 nm to about 1600 nm can be amplified with substantially the same gain. In other words, by using the optical fiber having high non-linearity, the required gain can be obtained even with a short optical fiber. Further, since the optical fiber can be shortened, a Raman amplifier which can be unitized can be provided.

Claims

1. A Raman amplifier including a pumping means comprising a plurality of pumping light sources and in which optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber, wherein:

said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and the wavelengths interval between pumps is greater than 6 nm and smaller than 35 nm.

2. A Raman amplifier including a pumping means comprising a plurality of pumping light sources and in which optical signals propagated through an optical fiber are Raman amplified by the pumping light sources coupled into the fiber, wherein:

said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and the wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm; and further including:

a controlling means for maintaining the amplifier output power to a predetermined value by adjusting each pump powers from the pumping means on the basis of a result given by the amplifier input or output monitoring means.

3. A Raman amplifier including a pumping means comprising a plurality of pumping light sources and in which optical signals propagated through an optical fiber are Raman amplified by the pumping light sources coupled into the fiber, wherein:

said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and the wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm; and further including:

a controlling means for flattening wavelength dependency of the amplifier output by adjusting each pump powers from the pumping means on the basis of a result given by the amplifier input or output monitoring means.

4. A Raman amplifier including a pumping means comprising a plurality of pumping light sources and in which optical signals propagated through an optical fiber are Raman amplified by the pumping light sources coupled into the fiber, wherein:

said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and the wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm; and further including:

a controlling means for maintaining the amplifier gain to a predetermined value by adjusting each pump powers from the pumping means so as to keep a ratio between the amplifier input and output powers constant on the basis of a result given by the amplifier input or output monitoring means.

5. A Raman amplifier including a pumping means comprising a plurality of pumping light sources and in which optical signals propagated through an optical fiber are Raman amplified by the pumping light sources coupled into the fiber, wherein:

said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and the wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm; and

said optical fiber, in which optical signals are Raman-amplified, has non-linear index n_2 of refraction of $3.5E-20$ [m²/W] or more.

6. A Raman amplifier including a pumping means comprising a plurality of pumping light sources and in which optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber, wherein:

said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and the wavelength interval between the

pumps is greater than 6 nm and smaller than 35 nm; and
said optical fiber, in which optical signals are Raman-amplified, exists as a part of a transmission line.

7. A Raman amplifier including a pumping means comprising a plurality of pumping light sources and in which optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber, wherein:

said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and the wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm; and
said optical fiber, in which optical signals are Raman-amplified, comprises a standard single fiber (SMF) and a fiber having dispersion of less than -20/ps/nm/km.

8. A Raman amplifier including a pumping means comprising a plurality of pumping light sources and in which optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber, wherein:

said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and the wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm; and
said optical fiber, in which optical signals are Raman-amplified, exists independent of a transmission line and can be inserted into said transmission line.

9. An optical repeater adapted to be inserted into a transmission line so as to compensate loss in said transmission line, comprising:

a Raman amplifier including a pumping means comprising a plurality of pumping light sources and in which the optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber, wherein said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm.

10. An optical repeater adapted to be inserted into an optical fiber transmission line so as to compensate loss in said optical fiber transmission line, comprising:

a Raman amplifier including an pumping means comprising a plurality of pumping light sources and in which the optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber, wherein said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm;
and further including:

a controlling means for maintaining the amplifier output power to a predetermined value by adjusting each pump powers from the pumping means on the basis of a result given by the amplifier input or output monitoring means.

11. An optical repeater adapted to be inserted into an optical fiber transmission line so as to compensate loss in said optical fiber transmission line, comprising:

a Raman amplifier including an pumping means comprising a plurality of pumping light sources and in which the optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber, wherein said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or an MOPAs, and the central wavelengths of the pumps are different from each other and wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm;
and further including:

a controlling means for flattening wavelength dependency of the amplifier output by adjusting each pump powers from the pumping means on the basis of a result given by the amplifier input or output monitoring means.

12. An optical repeater adapted to be inserted into an optical fiber transmission line so as to compensate loss in said

optical fiber transmission line, comprising:

a Raman amplifier including an pumping means comprising a plurality of pumping light sources and in which the optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber, wherein said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or an MOPAs, and the central wavelengths of the pumps are different from each other and wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm;

and further including:

a controlling means for maintaining the amplifier gain to a predetermined value by adjusting each pump powers from the pumping means so as to keep a ratio between the amplifier input and output powers constant on the basis of results given by the amplifier input and output monitoring means.

13. An optical repeater adapted to be inserted into an optical fiber transmission line so as to compensate loss in said optical fiber transmission line, comprising:

a Raman amplifier including an pumping means comprising a plurality of pumping light sources and in which the optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber, wherein:

said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm, and

said optical fiber, in which optical signals are Raman-amplified, has non-linear index n_2 of refraction of $3.5E-20$ [m²/W] or more.

14. An optical repeater adapted to be inserted into an optical fiber transmission line so as to compensate loss in said optical fiber transmission line, comprising:

a Raman amplifier including an pumping means comprising a plurality of pumping light sources and in which the optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber,

wherein:

said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm, and;

said optical fiber, in which optical signals are Raman-amplified, exists as a part of a transmission line.

15. An optical repeater adapted to be inserted into an optical fiber transmission line so as to compensate loss in said optical fiber transmission line, comprising:

a Raman amplifier including an pumping means comprising a plurality of pumping light sources and in which the optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber,

wherein:

said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm, and

said optical fiber, in which optical signals are Raman-amplified, comprises a standard single mode fiber (SMF) and a fiber having dispersion of less than -20/ps/nm/km.

16. An optical repeater adapted to be inserted into an optical fiber transmission line so as to compensate loss in said optical fiber transmission line, comprising:

a Raman amplifier including an pumping means comprising a plurality of pumping light sources and in which the optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber,

wherein:

said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or an MOPAs, and the central wavelengths of the pumps are different from each other and wavelength interval between the pumps is

greater than 6 nm and smaller than 35 nm, and

said optical fiber, in which optical signals are Raman-amplified, exists independent of a transmission line and can be inserted into said transmission line.

- 5 17. An optical repeater adapted to be inserted into a transmission line so as to compensate loss in said transmission line, comprising:

10 a Raman amplifier including a pumping means comprising a plurality of pumping light sources and in which optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber, wherein said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm;

and further comprising:

15 rare earth doped fiber amplifier disposed at the preceding or following stage or both stages to said Raman amplifier.

18. An optical repeater adapted to be inserted into a transmission line so as to compensate loss in said transmission line, comprising:

20 a Raman amplifier including a pumping means comprising a plurality of pumping light sources and in which optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber, wherein said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm;

25 and further comprising:

rare earth doped fiber amplifier disposed at the preceding or following stage or both stages to said Raman amplifier; and

30 a controlling means for maintaining the repeater output power to a predetermined value by adjusting each pump powers from the pumping means on the basis of a result given by the repeater input or output monitoring means.

19. An optical repeater adapted to be inserted into a transmission line so as to compensate loss in said transmission line, comprising:

35 a Raman amplifier including a pumping means comprising a plurality of pumping light sources and in which optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber, wherein said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm;

40 and further comprising:

rare earth doped fiber amplifier disposed at the preceding or following stage or both stages to said Raman amplifier; and

45 a controlling means for flattening wavelength dependency of the repeater output by adjusting each pump powers from the pumping means on the basis of a result given by the repeater input or output monitoring means.

20. An optical repeater adapted to be inserted into a transmission line so as to compensate loss in said transmission line, comprising:

50 a Raman amplifier including a pumping means comprising a plurality of pumping light sources and in which optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber, wherein said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm;

and further comprising:

55 rare earth doped fiber amplifier disposed at the preceding or following stage or both stages to said Raman amplifier; and

a controlling means for maintaining the amplifier gain to a predetermined value by adjusting each pump powers from the pumping means so as to keep a ratio between the repeater input and output powers constant on the

basis of results given by the repeater input and output monitoring means.

21. An optical repeater adapted to be inserted into a transmission line so as to compensate loss in said transmission line, comprising:

a Raman amplifier including a pumping means comprising a plurality of pumping light sources and in which optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber, wherein:

said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm; and

said optical fiber, in which optical signals are Raman-amplified, has non-linear index n_2 of refraction of 3.5×10^{-20} [m²/W] or more; and further comprising:

rare earth doped fiber amplifier disposed at preceding or following stage or both stages to said Raman amplifier.

22. An optical repeater adapted to be inserted into a transmission line so as to compensate loss in said transmission line, comprising:

a Raman amplifier including a pumping means comprising a plurality of pumping light sources and in which optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber, wherein:

said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm; and

said optical fiber, in which optical signals are Raman-amplified, exists as a part of said transmission line; and further comprising:

rare earth doped fiber amplifier disposed at preceding or following stage or both stages to said Raman amplifier.

23. An optical repeater adapted to be inserted into a transmission line so as to compensate loss in said transmission line, comprising:

a Raman amplifier including a pumping means comprising a plurality of pumping light sources and in which optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber, wherein:

said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm; and

said optical fiber, in which optical signals are Raman-amplified, comprises a standard single mode fiber (SMF) and a fiber having dispersion of less than -20 ps/nm/km; and further comprising:

rare earth doped fiber amplifier disposed at preceding or following stage or both stages to said Raman amplifier.

24. An optical repeater adapted to be inserted into a transmission line so as to compensate loss in said transmission line, comprising:

a Raman amplifier including a pumping means comprising a plurality of pumping light sources and in which optical signals propagated through an optical fiber are Raman-amplified by the pumping light sources coupled into the fiber, wherein:

said pumping means comprises semiconductor lasers of Fabry-Perot, DFB or DBR type or MOPAs, and the central wavelengths of the pumps are different from each other and wavelength interval between the pumps is greater than 6 nm and smaller than 35 nm; and

said optical fiber, in which optical signals are Raman-amplified, exists independent of said transmission line; and further comprising:

rare earth doped fiber amplifier disposed at preceding or following stage or both stages to said Raman amplifier.

25. An optical repeater according to any one of claims 17 to 24, wherein a gain of said rare earth doped fiber amplifier is kept constant and a gain of the repeater is adjusted by a gain of said Raman amplifier.
26. An optical repeater according to any one of claims 17 to 24, wherein wavelength dependency of a gain of said rare earth doped fiber amplifier is compensated by using wavelength dependency of a gain of said Raman amplifier.
27. An optical repeater adapted to be inserted into a transmission line so as to compensate chromatic dispersion and loss in said transmission line, comprising:
a Raman amplifier in which pumping light sources are not wavelength-multiplexed; and
rare earth doped fiber amplifier disposed at preceding or following stage or both stages to said Raman amplifier;
and wherein
said Raman amplifier includes a dispersion compensating fiber in which optical signals are Raman-amplified.
28. An optical repeater according to claim 27, wherein a gain of said rare earth doped fiber amplifier is kept constant and a gain of the repeater is adjusted by a gain of said Raman amplifier.
29. A Raman amplification method by stimulated Raman scattering in an optical fiber through which two or more pumping lights having different central wavelengths and said optical signals are propagated, wherein:
the pumping power launched into said optical fiber increases as the central wavelength of said pumping lights is shorten.
30. A Raman amplification method by stimulated Raman scattering in an optical fiber through which two or more pumping lights having different central wavelengths and said optical signals are propagated, wherein:
the total pumping power on the shorter wavelength side with respect to the center between a shortest and longest central wavelength among said two or more pumping lights is greater than on the longer side.
31. A Raman amplification method by stimulated Raman scattering in an optical fiber through which three or more pumping lights having different central wavelengths and said optical signals are propagated, wherein:
the number of the pumping light sources on the shorter wavelength side with respect to the center between the shortest and longest central wavelength among said three or more pumping lights is greater than on the longer side, and the total pumping power on the shorter wavelength side is greater than on the longer side.




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6A




FIG. 6B




FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 11




FIG. 12

PUMPING
POWER

GAIN





FIG. 13A

FIG. 13B



IN ORDER NOT TO OVERLAP $\lambda_{pn} < \lambda_{s1}$



$$\lambda_{pn} - \lambda_{p1} < 100\text{nm}$$

FIG. 14





FIG. 15



$$\lambda_{s1} \approx \lambda_{p1} + 100\text{nm}$$

$$\lambda_{s2} \approx \lambda_{p2} + 100\text{nm}$$

$$\lambda_{s3} \approx \lambda_{p3} + 100\text{nm}$$

$$\lambda_{s4} \approx \lambda_{p4} + 100\text{nm}$$

FIG. 16

REPEATER SPECIFICATION	①	②	③
REPEATER INPUT P_{in} [dBm/ch]	-20 ± 3	-15 ± 2	-15 ± 1
REPEATER OUTPUT P_{out} [dBm/ch]	10	10	5
DCF LOSS L_d [dB]	10 ± 2	8 ± 1.5	6 ± 1

FIG. 17A

EDFA DESIGN EXAMPLE		①	②	③
AMPLIFIER 1 GAIN	G_1 [dB]	20 ± 3	15 ± 2	15 ± 1
AMPLIFIER 2 GAIN	G_2 [dB]	20 ± 2	18 ± 1.5	11 ± 1
REPEATER GAIN	G_r [dB]	30 ± 3	25 ± 2	20 ± 1

FIG. 17B




FIG. 18




FIG. 19A




FIG. 19B

SPECIFICATION	①	②	③
REPEATER INPUT	-20 ± 3	-15 ± 2	-15 ± 1
REPEATER OUTPUT	+10	+10	+5
DCF LOSS	10 ± 2	8 ± 1.5	6.5 ± 1

FIG. 20A

AMPLIFIER 1	13	13	13
AMPLIFIER 2	10	10	10
RAMAN GAIN	17 ± 5	10 ± 3.5	3 ± 2
REPEATER GAIN	30 ± 3	25 ± 2	20 ± 1

FIG. 20B

COMPENSATION FOR INPUT LEVEL FLUCTUATION
DUE TO RAMAN AMPLIFYING EFFECT




FIG. 21A

COMPENSATION FOR FLUCTUATION IN LOSS OF
DCF DUE TO RAMAN AMPLIFYING EFFECT




FIG. 21B




FIG. 22




FIG. 23




FIG. 24




FIG. 25




FIG. 26




FIG. 27




FIG. 28




FIG. 29




FIG. 30




FIG. 31




FIG. 32




FIG. 33




FIG. 34




FIG. 35




FIG. 36




FIG. 37




FIG. 38




FIG. 39




FIG. 40




FIG. 41




FIG. 42




FIG. 43




FIG. 44




FIG. 45




FIG. 46
PRIOR ART




FIG. 47




FIG. 48




FIG. 49




FIG. 50




FIG. 51




FIG. 52




FIG. 53

THIS PAGE BLANK (USPTO)

INTERNATIONAL SEARCH REPORT

International application No.

PCT/JP99/03933

A. CLASSIFICATION OF SUBJECT MATTER Int.Cl. ⁶ G01R31/26		
According to International Patent Classification (IPC) or to both national classification and IPC		
B. FIELDS SEARCHED Minimum documentation searched (classification system followed by classification symbols) Int.Cl. ⁶ G01R31/26, H01L21/66, H01R33/76		
Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched Jitsuyo Shinan Koho 1926-1996 Toroku Jitsuyo Shinan Koho 1994-1999 Kokai Jitsuyo Shinan Koho 1971-1999 Jitsuyo Shinan Toroku Koho 1996-1999		
Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)		
C. DOCUMENTS CONSIDERED TO BE RELEVANT		
Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	JP, 9-178806, A (Hitachi, Ltd., et al.), 11 July, 1997 (11. 07. 97), Full text ; Figs. 1 to 10 (Family: none)	1-13
A	JP, 10-82826, A (Fujitsu Ltd., et al.), 31 March, 1998 (31. 03. 98), Full text ; Figs. 1 to 11 (Family: none)	1-13
A	JP, 7-218584, A (Fujitsu Ltd., et al.), 18 August, 1995 (18. 08. 95), Full text ; Figs. 1 to 7 (Family: none)	1-13
E, A	JP, 11-233220, A (Yutaka Ootsubo, Makoto Matsumura), 27 August, 1999 (27. 08. 99), Full text ; Figs. 1 to 6 (Family: none)	1-13
<input type="checkbox"/> Further documents are listed in the continuation of Box C. <input type="checkbox"/> See patent family annex.		
* Special categories of cited documents: "A" document defining the general state of the art which is not considered to be of particular relevance "E" earlier document but published on or after the international filing date "L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified) "O" document referring to an oral disclosure, use, exhibition or other means "P" document published prior to the international filing date but later than the priority date claimed "T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention "X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone "Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art "Z" document member of the same patent family		
Date of the actual completion of the international search 19 October, 1999 (19. 10. 99)		Date of mailing of the international search report 2 November, 1999 (02. 11. 99)
Name and mailing address of the ISA/ Japanese Patent Office		Authorized officer
Facsimile No.		Telephone No.

Form PCT/ISA/210 (second sheet) (July 1992)

THIS PAGE BLANK (USPTO)